


# Pclix™ Quick Programming Guide

- ● If an option is set ON then the
- ● LED startup sequence will flash
- ● as indicated under LF Dial.

To enter Programming Mode turn OFF Pclix LT100, Hold down red FIRE button, turn ON Pclix LT100, wait for 3 RED flashes to finish, release red Fire button. V1.6

LF Dial	User Option	RT Dial and Steps for Programming Sequence
<input type="radio"/> 0 <span style="color: green;">●</span> <input type="radio"/> <span style="color: green;">●</span> <input type="radio"/> <span style="color: green;">●</span>	Split Second Off/On	Set RT Dial 0=OFF 1=ON, Enter Programming Mode, release FIRE button, after 4 Green flashes turn OFF Pclix LT100.
<input type="radio"/> 1 <span style="color: green;">●</span> <input checked="" type="radio"/> <span style="color: red;">●</span> <input type="radio"/> <span style="color: green;">●</span>	Delay Start Off/On	Set RT Dial 0=OFF 1=ON, Enter Programming Mode, release FIRE button, after 4 Green flashes turn OFF Pclix LT100.
2	Set Delay Start Length	Enter Programming Mode, release Fire button, after 1 Green flash set the Hours, push Fire button, after 2 Green flashes set the Minutes, push FIRE button, after 3 Green flashes set the Seconds, push FIRE button, after 4 Green flashes turn OFF.
<input type="radio"/> 3 <span style="color: green;">●</span> <input checked="" type="radio"/> <span style="color: red;">●</span> <input type="radio"/> <span style="color: green;">●</span>	Image Count Off/On	Set RT Dial 0=OFF 1=ON, Enter Programming Mode, release FIRE button, after 4 Green flashes turn OFF Pclix LT100.
4	Set Image Count	Enter Programming Mode, release Fire button, after 2 Green flashes set the Thousands & Hundreds, push FIRE button, after 3 Green flashes set the Tens & Ones, push FIRE button, after 4 Green flashes turn OFF Pclix LT100. <span style="float: right;">See Over -&gt;</span>

LF Dial	User Option	RT Dial and Steps for Programming Sequence
	Bulb Option Off/On	Set RT Dial 0=OFF 1=ON, Enter programming mode, release FIRE button, after 4 Green flashes turn OFF Pclix LT100.
6	Set Bulb Length	Enter programming mode, release FIRE button, after 2 Green flashes set the Minutes, push FIRE button, after 3 Green set the Seconds, push FIRE button, after 4 Green flashes turn OFF the Pclix LT100.
7	Set Camera Model	Set the RT Dial to desired Camera Model (see user manual for details) Enter programming mode, release FIRE button, after 4 Green flashes turn OFF Pclix LT100.
8	Not Used	If selected you will get an error warning.
9	Set User Intervals	Set RT Dial to a register from 0-9, Enter programming mode, after 1 Green flash set the Hours, push Fire button, after 2 Green flashes set the Minutes, push FIRE button, after 3 Green flashes set the Seconds, push FIRE button, after 4 Green flashes turn OFF the Pclix LT100.

This Guide is meant to be a quick reference only, for detailed operating instructions for the Pclix LT100 please see your user manual or download it from our website.



[www.pclix.com](http://www.pclix.com)

copyright©2006 1017 Visual Effects Inc.

See Over ->